4-UNIVERSE CRMX TRANSMITTER WITH SACN / ART-NET NODE

SKT4 TRANSMITTER

Four independent CRMX universes plus a built-in network node — feed it sACN or Art-Net straight from the console.



The SKT4 is four wireless transmitters and a network node in one box. Each of its four CRMX universes pairs independently to compatible receivers, and the built-in sACN/E1.31 and Art-Net node means the source can be a lighting network instead of four DMX lines — one RJ45 from the switch and you're on air. Configuration runs over the network using DMXKing software. Power comes in on Neutrik PowerCon or straight over PoE.

4 universes | sACN / Art-Net | PoE 802.3af | PowerCon

FEATURES

- Four independent CRMX universes — 512 channels each
- Each universe pairs independently to any CRMX-compatible receiver
- Built-in sACN/E1.31 and Art-Net node on RJ45
- Network configuration via DMXKing software
- Powered by 90–240 V AC on Neutrik PowerCon or PoE (IEEE 802.3af)
- Four external antennas on RP-TNC

SPECIFICATIONS

DMX CAPACITY	4 universes (512 channels each)
RADIO	LumenRadio CRMX (TimoTwo)
NETWORK PROTOCOLS	sACN / E1.31, Art-Net
CONFIGURATION	RJ45, DMXKing software
POWER	90–240 V AC 50/60 Hz (Neutrik PowerCon) or PoE IEEE 802.3af
DIMENSIONS	190 × 120 × 55 mm (7.4 × 4.7 × 2.2 in)

IN THE BOX

- SKT4 TX transmitter with integrated network node
- 4 × antennas
- PowerCon feeder cord